



電錶讀取器

WFX 09

Protocols

802.11b/g/n

Center frequency range

2412 - 2484 MHz

Antenna

Built-in or SMA output

Power Input

Voltage Range

18 - 48V (normal 24V) / PoE

Input Current

0.2A max.

Other interface

LED x 5

One LED for RS485 Status.

One LED for Internet Status.

One LED for AP Mode indication.

Two LEDs for the TX and RX of USB.

One Power LED.

AP Button

Long press 3 seconds will enter the AP mode for setting the SSID and Password of WiFi.

Reset Button.

Reset the System.

Sensor

A 相電流 / A 相電壓 / B 相電流 / B 相電壓 / C 相電流 /

C 相電壓 / 累積電量 / 總電量 / 即時電量

1 可以即時讀取電錶數值。

2 讀取器擁有自己的網頁，
可以呈現電錶數值。

3 WiFi 通訊方式，無需網
路佈線。

4 適合 WiFi AP 已經滿佈
的場域中使用。

5 適用 18 - 48V 或是 PoE
進行供電。